


READ ME FIRST

Macintosh®



***DSL Equipment Installation Guide: Efficient Networks® 5260**



***Digital Subscriber Line**

Part Number: 5260MC02

Version 1.2

©2001 SBC Advanced Solutions, Inc. All rights reserved.

Table of Contents

Follow Steps 1 through 8 to complete the DSL Equipment Installation

Step 1: Verify Your System Requirements and Documents	2
Step 2: Verify the Contents of Your DSL Equipment Kit	3
Step 3: Install a Telephone Filter on Every Telephone Line	4
Step 4: Choose Your Modem and Minimum Requirements Check	8
Step 5: Installing the Ethernet Hardware	11
Step 6: Install the Efficient Networks® DSL Modem	12
Step 7: Finish Configuring your System	14
Step 8: Follow Internet Service Provider Instructions	16
APPENDICES	17
Having Trouble?	18
Installing the Ethernet Hardware	19
DESKTOP Systems - Installing the Ethernet Adapter	20
LAPTOP Systems - Installing the Ethernet Adapter	22
Uninstalling/Reinstalling the Ethernet Adapter	23
Troubleshooting SBC Express	24

For Support:

- Review the **troubleshooting** in this guide on **page 18**.
- Call your Internet Service Provider 'help desk' for further information on Internet Service Provider connection, and registration.

IMPORTANT NOTE: This guide portrays the typical flow for the installation process. Please follow the instructions, including running the SBC Express software **BEFORE** installing any NIC cards or modems. Some computer or network configurations may cause software windows to appear that are not depicted in this guide. Please read and follow the instructions on those screens to continue the installation process.

Verify that you are installing your DSL equipment AFTER the “Service Completion Date” given to you when you ordered your DSL Internet Service.

SBC Advanced Solutions, Inc. and affiliates have no responsibility for any personal injury or property damage which may result from your installation of DSL Equipment as discussed in this Guide. SBC Advanced Solutions, Inc. and its affiliates specifically disclaim any liability for such injury or damage. By proceeding with this installation, you assume all risk of personal injury or property damage. Please consult the documentation provided by your PC vendor to identify any impacts to your warranty. SBC, SBC EXPRESS and the SBC Logo are registered trademarks of SBC Communications, Inc.

Step 1: Verify Your System Requirements and Documents

This Installation Guide is for Macintosh® users only.

The SBC Express installation software will ensure that you meet the following minimum requirements. You will not be able to complete the installation without meeting these requirements.

- **Macintosh®** system with any one of the following:
 - a) A built-in Ethernet port (consult your system's documentation for details)*
 - b) An available PCI slot (if Ethernet port not available)
 - c) An available PCMCIA slot and a floppy disk drive


***Please note: many Macintosh® systems already have a Network Interface Card installed. The SBC Express software will detect if you have a Network Interface Card installed. If your system already has a card installed, you DO NOT need to install an additional one. If you have any questions, please consult the information that came with your Macintosh® system.**

Other items you may need during the installation process:

- Your system manufacturer Owner's Manual.
- Documentation and/or software from your Internet Service Provider.

Call your Internet Service Provider if you have questions regarding System Requirements or System Documentation.

Step 2: Verify the Contents of Your DSL Equipment Kit



Your DSL Equipment Kit Contains:

A: This Installation Guide and the SBC Express Installation CD.

B: 1 Efficient Networks® 5260 DSL Modem with Ethernet cable (connects to Adapter, below), and power cable.

C: 1 Filter Pack containing: 5 in-line filters, 1 wall-mount filter, 1 two-way adapter, and 1 data cable.

D: 1 Ethernet Adapter for Desktop Macintosh (if included in initial order)

--OR--


E: 1 Ethernet Adapter for Laptop Macintosh (if included in initial order)

Note: *Internet Software and/or instructions may be provided in this box or separately by your Internet Service Provider.*


Step 3: Install a Telephone Filter on Every Telephone Line

3-1 Set up the phone jack where your DSL modem will go.


1) Locate the phone jack where you want to connect your DSL




2) Insert the 2-way adapter in the phone jack



3) Connect a filter to one side of the 2-way adapter




4) If you have a phone, fax machine, analog modem or other phone device at this location, connect it to the filter



5) Connect the data cable that will go to your DSL modem to the unfiltered side of the 2-way adapter

To the DSL modem




3-2 Install a filter on all other phones and phone devices.




Why do I need a filter on all my other phones and phone devices?

Converting your regular phone line into a high-speed Digital Subscriber Line (DSL) can cause audible noise (high pitched tones and static) when you talk on the phone. You need to install a filter on every telephone or device that shares the same phone number as your DSL line to eliminate this noise.


Other phones




Answering machines




Caller ID boxes



Analog computer modems





Fax machines





Wall mount phones

Use the wall mount filter shown



Remember! Don't install a filter on the data cable that you are connecting to your DSL modem.

3-3 Other filters you may encounter in your DSL Equipment Kit.



Step 4: Choose Your Modem and Minimum Requirements Check


- 4-1 Insert the SBC Express CD into your CD-ROM drive. Double click the “SBC Express” icon to begin the installation process.




- 4-2 SBC Express displays the Welcome screen. Select the **Efficient 5260** then click **Next**.




- 4-3 SBC Express displays the Welcome screen. Click **Start** to proceed.



- 4-4 SBC Express displays the license agreement. If you agree to the terms, click **Accept**. If you do not accept, installation cannot continue.



- 4-5 SBC Express quickly checks your computer system to ensure that it meets the minimum requirements for DSL service. Click **Next** to proceed if you meet all requirements.



If your computer meets the minimum requirements, SBC Express automatically proceeds to the next step. You should continue to Step 6 on page 12.

If you shutdown your computer, **leave the CD in the CD-ROM drive**, and SBC Express will continue after you restart.


If your computer does not meet the minimum requirements, SBC Express displays a message with details of the problem. Your computer must meet the minimum requirements before you proceed.

If your computer fails the minimum requirements check because it does not have a Ethernet Adapter installed, please go to Appendix B on page 19.

If your network card is incorrectly installed, SBC Express will help you fix it. See *Troubleshooting SBC Express* on page 24 for help troubleshooting network card and minimum requirement problems.

Step 5: Installing the Ethernet hardware (if needed)

IMPORTANT NOTE: Most Macintosh computers already have an Ethernet card installed. If this is the case with your Macintosh, SBC Express would have reported that you passed the minimum requirements. If you see the following screen, or if you ordered the NIC-less kit, **it is not necessary to install the Ethernet Adapter** provided in this equipment package.




You may proceed directly to Step 6 on page 12 if you see the screen above. If not, you will need to install the Ethernet Adapter provided, and this requires that you open your computer. Please follow the instructions in Appendix B and consult the documentation provided by your computer vendor to identify any impacts to your warranty.


Step 6: Install the Efficient Networks® DSL Modem

Your computer should be turned on. Your modem should be turned OFF.

You should be at the following screen in the SBC Express Installation Software:




6-1 Consult the following diagram to install your modem.



- 6-2 Plug the power cable into the DSL modem and an electrical outlet.
- 6-3 Connect the data cable to your telephone jack and your DSL modem. There should NOT be a filter between the data cable and the wall jack.
- 6-4 Connect the Ethernet cable to the Ethernet Port or the built –in Ethernet Port on the back or side of your Macintosh and to the Ethernet Port on the back of your DSL modem.
- 6-5 Turn the DSL Modem power switch **ON**.
- 6-6 The **Sys**, **ATM**, **Enet** and **DSL** lights should all turn solid green within two minutes.
- If the **Sys** or **ATM** light does not turn solid green, check your power cable. Are you connected to a live electrical outlet? Are connections secured? Is the modem turned on?
 - If the **Enet** light does not turn solid green, check your Ethernet connections. Are they secure? Is the Macintosh turned on?
 - If the **DSL** light does not turn solid green:
 - Verify that there is NO in-line filter on the data cable from your DSL modem to the telephone jack.
 - Try another telephone jack in your home.
 - Turn off the modem, reboot the computer and then turn the modem back on.
 - Verify that you are installing your DSL equipment AFTER the “Service Completion Date” given to you when you ordered your DSL Internet Service.
 - If none of these steps cause the DSL light to turn green, please call your Internet Service Provider 'help desk'.
- 6-7 Proceed to Step 7 by clicking **Next** on the DSL Modem Setup screen.


Step 7: Finish Configuring Your System

- 7-1 SBC Express now prompts you for your first and last name. Please type your first and last name and then click **Next** to proceed.




The screenshot shows the 'SBC Express' window with a blue background on the left containing the SBC logo and 'BroadJump POWERED' text. The main area is titled 'Subscriber Information'. It contains a checkbox labeled 'I am installing this product myself' which is checked. Below this is a 'Technician Name' field with 'Self Install' entered. Underneath is a 'User Information' section with 'First Name' and 'Last Name' fields. At the bottom, there is a note: 'If you are the end user running this program yourself, click to check this box.' and a statement 'Fields in bold are required.' The window has 'Cancel' and 'Next' buttons at the bottom.

- 7-2 Enter your 10-digit phone number in the next screen. Click **Next** to proceed.



The screenshot shows the 'SBC Express' window, similar to the previous one, but the 'Subscriber Information' section now only contains a 'Phone Number' field. The 'I am installing this product myself' checkbox is no longer visible. The 'User Information' section is also absent. The 'Fields in bold are required.' note remains at the bottom. The window now includes 'Cancel', 'Details', and 'Next' buttons at the bottom.

- 7-3 Congratulations! You have finished setting up your DSL hardware. Click **Quit** in SBC Express and then proceed to Step 8.



***Step 8:* Follow the Instructions Supplied by your Internet Service Provider**

Your Internet Service Provider may have provided you additional instructions in this box or separately. These instructions may contain information about account setup, additional software installation, and/or Internet usage. Please follow those instructions to complete your Internet connection setup. Your Internet Service Provider will offer technical assistance if you need help connecting to the Internet.

Appendices

APPENDIX A

Having Trouble?

If the suggestions below don't resolve your problem, technical support is available from your Internet Service Provider. Please refer to the Internet Service Provider's information on how to contact them for technical assistance.

I can't open my computer case. What do I do?

- Consult your computer manufacturer's Owner's Manual.
- Call your computer manufacturer's Support Line.

I can't connect. What do I do?

- Make sure there is no filter on the phone jack/cord connected to your DSL modem
- Check your Ethernet cable connection. Is it secure?
- Verify that you are installing your DSL equipment AFTER the "Service Completion Date" given to you when you ordered your DSL Internet Service.
- Call your Internet Service Provider 'help desk' for further information on Internet Service Provider connection, and registration.

APPENDIX B: Installing the Ethernet hardware (if needed—see Step 5)

IMPORTANT NOTE: If your computer already has an Ethernet card installed and you passed the minimum requirements step in the SBC Express Installation Software, it is not necessary to install the Ethernet Adapter provided in this equipment package. If you have a newer Macintosh (iMac®, iBook®, and G4 Cube®) with a built in Ethernet port you do not need to install the provided Ethernet Adapter.


If you shutdown your computer, **leave the CD in the the CDRom drive**, and SBC Express will continue after you restart.

Installing the Ethernet Adapter

- Follow steps B-1 through B-10 below for **Desktop** Macintosh installations.
- For **Laptops**, skip to step B-11.


DESKTOP Systems

- B-1 **Click Quit in SBC Express and then turn off all peripheral devices. Remember to leave the SBC Express CD in the CD-ROM drive.**
- B-2 Unplug the power cord for your computer from the electrical outlet.
- B-3 Open the case of your computer (review your computer manufacturer's Owner's Manual for specific instructions).
- B-4 Touch the computer chassis (metal frame) before touching the Ethernet Adapter. This helps to protect the Ethernet Adapter from static electricity.
- B-5 Locate an available PCI slot (usually white in color). You may use any available PCI slot. Make sure you are looking downwards on the PCI slot. You may need to turn the computer on its side to accomplish this (*review your computer manufacturer's Owner's Manual for specific instructions*).
- B-6 Remove the metal PCI slot cover from the unused PCI slot, and retain the screw.



- B-7 Carefully insert the Ethernet Adapter into any empty PCI slot. Make sure the card is completely seated by pressing firmly.

- B-8 Verify that the end bracket is flush against the chassis. Make sure the gold connectors along the base of the Ethernet Adapter are completely and evenly inserted into the PCI slot.




- B-9 Fasten the card into the computer chassis with the screw you set aside earlier.
- B-10 Replace the computer cover. Plug the power cord back into the electrical outlet and turn on your Macintosh, making sure the SBC Express CD is in the CD-ROM drive. Proceed to step B-14.

LAPTOP Systems- Installing the Ethernet Adapter

B-11 **Click Quit in SBC Express and then turn off all peripheral devices. Remember to leave the SBC Express CD in the CD-ROM drive.**

B-12 Insert the Ethernet Card into your computer's PCMCIA Type II or Type III slot.



B-13 Carefully push the Media Access Module (MAM) into the socket on the Card until the locking tabs click into place.

B-14 Power up your laptop after making sure the SBC Express CD is still in the CD-ROM drive.

Appendix C

I want to uninstall/reinstall the Ethernet Adapter. What do I do?

DESKTOP: For the Internal Ethernet Adapter Card:

- Open the computer case using your computer manufacturer's instructions and then remove the screw holding card in place.
- Carefully remove the Ethernet Adapter card from the PCI slot.

LAPTOP For the PCMCIA Card

- Press the release button (consult your computer manufacturer's Owner's Manual if you don't know where this button is located).
- Slide the Card completely out of the slot.

Reinstall the card following procedures in Step 4. Desktop users should try a different PCI slot, if possible.

APPENDIX D

Troubleshooting SBC Express

Please refer to this list if you are having problems using SBC Express or if you receive an error message. If after troubleshooting, you are still having problems, then you should contact your Internet Service Provider 'help desk' for further information

Step	Problem	Solution
Minimum Resources	SBC Express verifies minimum requirements on several resources including hard drive space, RAM, operating system level, and processor speed and family. If any of these resources are under the required value, an error will display describing which resource did not meet the requirement.	Update your computer to the recommended resource level.
Installing Network Interface Card	When installing Network Interface Cards the installation process may ask for the original installation disk.	You may have to provide an installation CD-ROM for the installation of the drivers to be successful.
Incompatible Adapter	This scenario can occur when a machine had a previous NIC or Network Adapter installed, but the physical device is missing or was misconfigured.	Use the “Fix” button to launch the appropriate system control panel along with context sensitive help. The help provided will guide you through the steps to disable or remove the adapter.
Missing Internet Protocol	This scenario can occur if Client for Microsoft Networks is not installed with the TCP/IP protocol or if the NIC is installed without binding TCP/IP to the NIC.	Use the “Fix” button to launch the appropriate control panel and context sensitive help to guide you in binding TCP/IP to the network adapter.
Disabled Network Adapter	This scenario can occur when a NIC is present in the system, yet the adapter has been disabled.	Use the “Fix” button with context sensitive help to guide you through enabling the adapter.
Ping Test	The Ping Test is usually accomplished within the Configure TCP/IP step, where SBC Express pings the default gateway. An explicit IP address can also be used.	Failure during this test can occur from invalid network settings, the Ethernet cable not being plugged in, the DSL modem not being in synch, or if the specified IP address does not allow a ping. Make sure your Ethernet cable is plugged in and powercycle your DSL modem. Use the “Retry” button to try the test again.
DNS Test	The DNS Test will determine the currently defined DNS servers, attempt to ping them, and upon a successful ping, will resolve a specified hostname to an IP address.	This test can fail if the DNS server is invalid. If you entered static IP information, ensure you entered the DNS servers correctly.

This concludes the DSL Equipment Installation Guide